

Release Notes

Basic Information

Product Model	ADS NX3-M1600E
Software Version	V4.5R90F01SP01
Upgrade File	update_adsm_V4.5R90F01SP01build20181031.zip (MD5: 59da52bb131f7320bb6ad8918202a908)
Release Date	2018-11-05
How to Obtain	Contact NSFOCUS technical support.

Version Mapping

Source Software Version	V4.5R90F00SP04 V4.5R90F01
Product Model	ADS NX3-M1600E
Managed Device	ADS: V4.5.88.15.sp13 through V4.5.88.15.sp15 V4.5R89F03 through V4.5R89F03SP03 V4.5R90F00 through V4.5R90F00SP05 V4.5R90F01, V4.5R90F01SP01 NTA: V4.5.61.2.BF19 through V4.5.61.2.BF21 V4.5R89F03 through V4.5R89F03SP02 V4.5R90F00 through V4.5R90F00SP05 V4.5R90F01, V4.5R90F01SP01
Client	Internet Explorer 11 Chrome Firefox
Other System or Tool	None
Documentation	NSFOCUS ADS M User Guide (V4.5R90F01)

Note:

Make sure that this version is used together with an ADS or NTA version listed in **Managed Device**; otherwise, the collaboration function will be unable to work properly.

Open Bugs

None

Function Changes

New functions

1. The function of automatically clearing the database is added.
2. The function of downloading the syslog and SNMP interface description document is added.

Modified Functions

1. Broader IPv6 support is implemented.
2. Traffic trend graphs are optimized.
3. As for data storage, the minimum data merging threshold is changed to 1.

Upgrade and Rollback Paths

This upgrade package is for the upgrade of ADS M from **V4.5R90F00SP04** or **V4.5R90F01**.

Note:

After being upgraded to V4.5R90F01SP01, ADS M cannot be rolled back to the source version.

Upgrade Procedure

Make sure that the current ADS M version is **V4.5R90F00SP04** or **V4.5R90F01**. If the current version is an earlier version, ask technical support personnel of NSFOCUS to upgrade it to **V4.5R90F00SP04** or **V4.5R90F01**.

To perform the upgrade, follow these steps:

Step 1 Log in to the web-based manager of ADS M.

Step 2 Choose **Administration > Local Settings > System Upgrade**.

The **System Upgrade** page appears.

- Step 3** Browse to the upgrade file `update_adsm_V4.5R90F01SP01build20181031.zip`. Then click **Upload**.
- Step 4** After the upgrade package is successfully uploaded and the version number is confirmed to be correct, click **OK** to start the installation.
- Step 5** After the system informs you that the upgrade is complete, click **OK** to restart the system.
If no message is displayed to indicate installation completion, please wait 3 minutes. Then the system will automatically restart.
- Step 6** Refresh the web-based manager. Click **About** in the upper-right corner of the manager to check the current system version.
- If **Product Version** is **V4.5R90F01SP01** and **Build Date** is **20181031**, the upgrade succeeded.
 - If **Product Version** is not **V4.5R90F01SP01** or **Build Date** is not **20181031**, the upgrade failed. In this case, contact technical support personnel of NSFOCUS.
- End

Notes

After ADS M is upgraded to **V4.5R90F01SP01**, you need to redeploy ADS Portal under **Administration > Third-Party Interface > Portal Configuration**.