

Release Notes

Basic Information

Product Model	ADS NX3-M1600E
Software Version	V4.5R90F00SP02
Upgrade File	update_adsm_V4.5R90F00SP02build20180328.zip (MD5: cde1de2b3aebfe9b00b75080a3ac5491)
Release Date	2018-03-30
How to Obtain	Contact NSFOCUS technical support.

Version Mapping

Source Software Version	<ul style="list-style-type: none"> • V4.5R90F00 • V4.5R90F00SP01
Product Model	ADS NX3-M1600E
Managed Device	<p>ADS:</p> <ul style="list-style-type: none"> • V4.5.88.15.sp13 • V4.5.88.15.sp14 • V4.5R89F03 through V4.5R89F03SP03 • V4.5R90F00 through V4.5R90F0SP02 <p>NTA:</p> <ul style="list-style-type: none"> • V4.5.61.2.BF19 through V4.5.61.2.BF21 • V4.5R89F03 through V4.5R89F03SP02 • V4.5R90F00 through V4.5R90F0SP02
Client	Internet Explorer 11, Chrome, or Firefox browser
Other System or Tool	N/A
Documentation	NSFOCUS ADS M User Guide (V4.5R90F00)

Note:

Make sure that this version is used together with an ADS or NTA version listed in **Managed Device**; otherwise, the collaboration function will be unable to work properly.

Open Bugs

N/A

Function Changes

New function

The regional security module is improved to adapt to ADS of the latest version.

Modified Functions

- The description of access keys under **Administration > User and Audit > User Management** is corrected.
- The problem that certain proxy accounts cannot be configured in certain circumstances is fixed.
- The problem that cloud-side authentication cannot proceed as expected in certain circumstances is fixed.
- The cluster management function is improved.

Upgrade and Rollback Paths

ADS M can be upgraded to V4.5R90F00SP02 from V4.5R90F00 or V4.5R90F00SP01.

Note:

After being upgraded to V4.5R90F00SP02, ADS M cannot be rolled back to the source version.

Upgrade Procedure

Make sure that the current ADS M version is V4.5R90F00 or V4.5R90F00SP01. If the current version is an earlier version, ask NSFOCUS technical support to upgrade it to V4.5R90F00 or V4.5R90F00SP01.

To perform the upgrade, follow these steps:

Step 1 Log in to the web-based manager of ADS M.

Step 2 Choose **Administration > Local Settings > System Upgrade**.

The **System Upgrade** page appears.

Step 3 Browse to the upgrade file **update_adsm_V4.5R90F00SP02build20180328.zip**. Then click **Upload**.

Step 4 After the upgrade package is successfully uploaded and the version number is confirmed to be correct, click **OK** to start the installation.

Step 5 After the system informs you that the installation is complete, click **OK** to restart the system service.

If no message is displayed indicating that the installation is complete, please wait 3 minutes. Then the system service will automatically restart.

Step 6 Refresh the web-based manager. Click **About** in the upper-right corner of the manager to check the current system version.

- If **Product Version** is **V4.5R89F00SP02** and **Build Date** is **20180328**, the upgrade succeeded.
- If **Product Version** is not **V4.5R89F00SP02** or **Build Date** is not **20180328**, the upgrade failed. In this case, contact NSFOCUS technical support.

---End

Notes

After ADS M is upgraded to V4.5R90F00SP02, you need to redeploy ADS Portal under **Administration > Third-Party Interface > Portal Configuration**.