

Release Notes

Basic Information

Device Model	ADS NX3-M1600E
Software Version	V4.5R90F01SP08
Upgrade File	update_adsm_V4.5R90F01SP08build20190924.zip (MD5: 870f18ba699c7ee59d03af02605e28a8)
Release Date	2019-10-11
How to Obtain	Contact NSFOCUS technical support.

Version Mapping

Source Software Version	<ul style="list-style-type: none"> • V4.5R90F01SP03 • V4.5R90F01SP04 • V4.5R90F01SP05 • V4.5R90F01SP06 • V4.5R90F01SP07
Product Model	ADS NX3-M1600E
Managed Device	<ul style="list-style-type: none"> • ADS versions for collaboration: V4.5.88.15.sp13–V4.5.88.15.sp15 V4.5R89F03–V4.5R89F03SP03 V4.5R90F00–V4.5R90F00SP05 V4.5R90F01–V4.5R90F01SP07 • ADS versions the adaptation applies to (other versions do not support ADS M's management of their region security): V4.5R90F01SP05, V4.5R90F01SP06, and V4.5R90F01SP07 • NTA versions for collaboration: V4.5.61.2.BF19–V4.5.61.2.BF21 V4.5R89F03–V4.5R89F03SP02 V4.5R90F00– V4.5R90F00SP05 V4.5R90F01–V4.5R90F01SP05 • NTA versions the adaptation applies to (other versions do not support ADS M's management of their region security): V4.5R90F01SP02–V4.5R90F01SP05
Client	<ul style="list-style-type: none"> • Internet Explorer 11 • Chrome • Firefox
Other System or Tool	N/A
Documentation	NSFOCUS ADS M User Guide (V4.5R90F01)

Note:

Make sure that this version is used together with an ADS or NTA version listed in **Managed Device**; otherwise, the collaboration function will be unable to work properly.

Open Bugs

None

Function Changes

New Functions

1. The Device Management module now allows configuration of a custom host.

Modified Functions

1. The functionality of the regional security module is optimized.
2. The definition of uniqueness of attack ports and attack events is modified.
3. The English web UI concerning email report scheduling is optimized.

Upgrade and Rollback Paths

The upgrade package is applicable to **V4.5R90F01SP03** through **V4.5R90F01SP07**.

Note:

After being upgraded to V4.5R90F01SP08, ADS M cannot be rolled back to the source version.

Upgrade Procedure

Make sure that the source version of ADS M is within the range of **V4.5R90F01SP03** to **V4.5R90F01SP07**. If not, contact NSFOCUS technical support for upgrade of the current version to a version within this range.

To perform the upgrade, follow these steps:

- Step 1** Log in to the web-based manager of ADS M.
- Step 2** Choose **Administration > Local Settings > System Upgrade**.
The **System Upgrade** page appears.
- Step 3** Click **Browse** and select the upgrade package file **update_adsm_V4.5R90F01SP08build20190924.zip**. Then click **OK**.
- Step 4** After the upgrade package is successfully uploaded and the version number is confirmed to be correct, click **OK** to start the installation.
- Step 5** After the system informs you that the upgrade is complete, click **OK** to restart the system.
- Step 6** Refresh the web-based manager. Click **About** in the upper-right corner of the manager to check the current system version.
 - If **Product Version** is **V4.5R90F01SP08** and **Build Date** is **20190924**, the upgrade succeeded.

- If **Product Version** is not **V4.5R90F01SP08** or **Build Date** is not **20190924**, the upgrade failed. In this case, contact NSFOCUS technical support.

----End

Notes

After ADS M is upgraded to **V4.5R90F01SP08**, you need to redeploy ADS Portal under **Administration > Third-Party Interface > Portal Configuration**.